

# **ADC-V515**

### **SPECIFICATIONS**

RECORDING COMPRESSION H.264

MAX RESOLUTION 1920x1080

IMAGE SENSOR 1/3", 2.12 MP, 1920x1080, HDR

LENS / ANGLE OF VIEW 3.19 mm, F2.2, 110°

LOW-LIGHT SENSITIVITY
O lux with IR

IR RANGE Up to ~15 ft (4.6 m)

IMAGE ADJUSTMENTS
Flip, brightness, contrast,
saturation, sharpness, exposure

WIRELESS CONNECTIVITY 802.11 b/g/n, 2.4 GHz

OPERATING TEMPERATURE 32° F - 104° F (0° C - 40° C)

OPERATING HUMIDITY
20% - 100% Non-condensing

MAX POWER CONSUMPTION 12 V - 1 A DC

DIMENSIONS (L X W X H)
2.8 x 2.3 x 3.1" (7.1 x 5.9 x 8.0cm)

#### REQUIREMENTS

POWER

12 V - 1 A DC power adapter (included)

NETWORK

2.4 GHz Wi-Fi connection to broadband Internet



# 1080p Indoor Wi-Fi Video Camera with HDR

Get smarter video alerts and high-quality live and recorded video with the ADC-V515. With night vision and High Dynamic Range (HDR), the ADC-V515 lets you see what's important – no matter the time of day or lighting conditions. Powerful Video Analytics from Alarm.com can detect and alert you to people, vehicles, and animals entering your property. Enjoy cloud-based storage of video clips or add an Alarm.com Stream Video Recorder or Smart View for Onboard Recording for 24/7 local recording (additional hardware required).

### **FEATURES**

- 110° field of view
- High Dynamic Range (HDR)
- Two-Way Audio
- 2.4 GHz Wi-Fi connection
- Works with the Alarm.com customer website and mobile app
- Continuous Local Recording
  - Smart View for Onboard Recording
  - Stream Video Recorder
- Video Analytics, Video Motion Detection, and sensor-triggered clips saved to the cloud

# **INCLUDED ACCESSORIES**

- Power Adapter
- Mounting Hardware

## **LED GUIDE**

	LED STATUS	DESCRIPTION
STATUS LED	Off	Power off
0	Flashing Red	Power on, camera booting
	Flashing Green	Local network connection
	Solid Green	Connected to Alarm.com
	Blinking Blue	WPS mode
	Blinking White	Wi-Fi Access Point mode
TROUBLE CONDITION	Solid Red	No local or Internet connection
FACTORY RESET	Alternating Red and Green	Camera resetting to factory default